

MULTI Protocols Keyboard Controller(WS-M311S)

- ※Set the address range of the MS series camera and decoder:0-255
- ※Directly control speed dome camera on OSD menu
- ※Operate the pan/tilt of speed dome camera to move in different speed level
- ※Initial setting are subject to change through the speed dome camera menu
- ※Manually control the Focus/Zoom/Iris of the camera
- ※Manually control the Playback/Pause/East Playback /Forward Backwards/Menu1,4,9,16 screen view/search of the DVR
- ※LED Display
- ※RS-485 multi protocols communication
- ※Power Input DC 12V



Specification	
Model No.	WS-M131S
Power Supply	
Power Supply	12VDC ±10%
Power Consumption	300mA MAX
FUNCTION	
P/T/Z Controller	YES
Lens Controller	Zoom/Focus/Iris
Control Manner	OSD Menu
DVR Controller	Search/Menu/1/4/9/16 Display
Joystick	3 Axis
Cruising Tracks	Pre-defined
Communication	RS-485, PELCO-D/P Protocol(2400,4800,9600)bps
Transmission	Max 1200M
ENVIRONMENT	
Operation Temperature	Temperature: - 10 ℃ - +55℃
Storage Temperature	Temperature: - 20 ℃ - +60℃
Operation Humidity	20% - 90% RH
MECHANICAL	
Dimension	330(W) X 190(H) X 43(L)mm
Weight Approx	1630g
※※※ Product specification are subject to change without notice ※※※	

www.winsafecctv.com